

Build Your Gun in 5 Steps:	Example One Gun Part# build:
Step 1: Choose Your Gun Style	OGH
Step 2: Select Your Amperage	OGH-4
Step 3: Choose Your Length (<i>built to your spec if needed</i>)	OGH-4-15
Step 4: Select Your Power Pin Connection	OGH-4-15M
Step 5: Customize Your Setup (<i>if required</i>)	s/up: 02-023-6, 408-045, 03-524, 401-6-62, 44315

Custom Gun Bodies – Gun Lengths and Setups. No Headaches.

If your application is unique, contact us and we'll build it to match – without any long delays

Gun Style	Gun Body	Amperage	Length	Power Pin Connection
(Kent consumables) OG-	1/2" Gun Body	2-	200amp	10- M Miller
(Kent consumables) OGH-	9/16" Gun Body	3-	300amp	12- K Kent
(Bernard consumables) OGB-	1/2" Gun Body	4-	400amp	15- T T4
(Bernard CF consumables) OGHB-	9/16" Gun Body	5-	500amp	20- L Lincoln
(Tregaskiss consumables) OGHTG-	9/16" Gun Body			25- E Euro
(Tweco consumables) OGHTW-	9/16" Gun Body			

Electrical Plug Options:			
01-001-182M - Miller	01-001-182L - Lincoln	01-001-182E - ESAB	182M - Kent (standard)



Standard configurations shown below. Need something different? We'll build it.					Liner (based on plug-end)	
Style-Amp xx-Length i-Power Pin	Gun Body	Contact Tip	Gas Head	Nozzle	M, K, E	T, L
OG-2-xxi	02-021-4	408-035	03-424	401-4-62	43115	44-3545-15
OG-3-xxi	02-021-5	408-035	03-424	401-6-62	43115	44-3545-15
OG-4-xxi	02-021-6	408-045	03-424	401-6-62	44315	44-116-15
OGB-2-xxi	02-021B-4	408-035	03-424B	401-4-62	43115	44-3545-15
OGB-3-xxi	02-021B-5	408-035	03-424B	401-6-62	43115	44-3545-15
OGB-4-xxi	02-021B-6	408-045	03-424B	401-6-62	44315	44-116-15
OGH-2-xxi	02-023-4	408-035	03-524	401-6-62	43115	44-3545-15
OGH-3-xxi	02-023-5	408-035	03-524	401-6-62	43115	44-3545-15
OGH-4-xxi	02-023-6	408-045	03-524	401-6-62	44315	44-116-15
OGH-5-xxi	02-023-8	408-062	03-524	401-6-62	44315	44-116-15
OGHB-2-xxi	02-023B-4	408-035	03-424B	401-6-62	43115	44-3545-15
OGHB-3-xxi	02-023B-5	408-035	03-424B	401-6-62	43115	44-3545-15
OGHB-4-xxi	02-023B-6	408-045	03-424B	401-6-62	44315	44-116-15
OGHB-5-xxi	02-023B-8	408-062	03-424B	401-6-62	44315	44-116-15
OGHTG-2-xxi	02-023-4	408T-035	404-3	401-6-62	43115	44-3545-15
OGHTG-3-xxi	02-023-5	408T-035	404-3	401-6-62	43115	44-3545-15
OGHTG-4-xxi	02-023-6	408T-045	404-3	401-6-62	44315	44-116-15
OGHTG-5-xxi	02-023-8	408T-062	404-3	401-6-62	44315	44-116-15
OGHTW-2-xxi	02-023T-5	14H-35	54A	24A62	43115	44-3545-15
OGHTW-3-xxi	02-023T-5	14H-35	54A	24A62	43115	44-3545-15
OGHTW-4-xxi	02-023T-6	14H-45	54A	24A62	44315	44-116-15
OGHTW-5-xxi	02-023T-8	14H-62	54A	24A62	44315	44-116-15

